



PC – Automatic Standby Shutdown

Installation (see picture):

- Plug your Desk Computer and other office appliances such as printers, monitors, scanners etc into any of the 4 **controlled** sockets of the extension lead. Plug any device requiring continuous power e.g. fax machine into the **always-on** socket.
- Stick the reset button conveniently on or near to your computer.

First time set up – power learning

- Plug the extension lead into a mains wall socket and switch ON.
- The operating light should flash slowly for 3 seconds then remain illuminated. (If it doesn't, press the button on the device for 4 seconds at least until the light starts flashing). The device is now in **power learning mode**.
- Place all your connected devices into Standby and wait for at least 30 seconds.
- Then press the button on the device to end the learning cycle. The light will turn off and the sockets are off.

-To turn ON the Sockets:

Press the reset button on the flying lead. The light on the Standby Shutdown will illuminate indicating all the controlled sockets are re-powered. Power up your computer system as usual. *

-To turn OFF:

Power down your desk computer as normal. After 1 minute the Standby Shutdown will **automatically** turn off the power to all the controlled sockets.

* *Note:* You may also press the button on the front of the Standby Shutdown device to re-enable the sockets.



Note: The Standby Shutdown will retain its memory after a loss of power.

If you wish to change the number of connected appliances you will need to re-enter the power learning cycle. Press the button on the front of the device for 4 seconds to clear the previously set power level.

The indicator light will start flashing ready. Then carry on from e.

Note: The Standby Shutdown will retain its memory after a loss of power.

Specification

Voltage: 240V~ 50Hz
 Max .current: 13A
 Max. load: 3kW
 Colour: Black/White
 Mains cable: 1.5m
 Sensor cable: 1.3m
 4 controlled sockets
 1 always ON socket
 Product code: ENER008

Power consumption in standby: <1W.